





Rutherford

ELECTRONICS CO.



**PULSE GENERATOR
MODEL B7B**



**8944 LINDBLADE ST.,
CULVER CITY,
CALIFORNIA**

PULSE GENERATOR

MODEL B7B

Serial No. _____

Price \$5.00

Rutherford

ELECTRONICS CO.

8944 LINDBLADE STREET

CULVER CITY, CALIFORNIA

TELEPHONE Upton 0-7393

TABLE OF CONTENTS

	PAGE NO.
GENERAL DESCRIPTION - - - - -	1
SPECIFICATIONS - - - - -	2
OPERATING INSTRUCTIONS - - - - -	3
Front Panel Controls - - - - -	3
Preliminary Instructions - - - - -	5
MAINTENANCE - - - - -	5
General - - - - -	5
Calibration - - - - -	6
Trouble Shooting - - - - -	6
Calibration Chart - - - - -	7
CIRCUIT DESCRIPTION - - - - -	8
Oscillator Section - - - - -	8
Delay Section - - - - -	9
Width Section - - - - -	9
Start Pulse Channel - - - - -	9
Stop Pulse Channel - - - - -	9
Output Section - - - - -	9
Power Supply Section - - - - -	10
CIRCUIT THEORY - - - - -	10
Free-running Multivibrator - - - - -	10
Monostable Multivibrator - - - - -	11
Blocking Oscillator - - - - -	12
Schmitt Trigger - - - - -	13
PARTS LIST - - - - -	14
COMPONENT REPLACEMENT - - - - -	18
WARRANTY - - - - -	18
CIRCUIT BLOCK DIAGRAM - - - - -	following 18
CIRCUIT SCHEMATIC DIAGRAMS - following CIRCUIT BLOCK DIAGRAM	

PULSE GENERATOR

MODEL B7B

GENERAL DESCRIPTION

The model B7B is a compact, lightweight, general purpose pulse generator designed to meet the rigid requirements of a great number of research and test applications. Exacting design criteria, an electron tube complement of a small number of tube types, and special duty cycle limiting circuitry to automatically protect the output tubes from life-shortening overloads insure long periods of reliable operation with a minimum of maintenance and repair problems.

The model B7B produces trains of 50 volt pulses having repetition rates to 2 megacycles, pulse delays and widths to 10,000 microseconds, and rise and fall times of 15 millimicroseconds, and a permissible duty factor of up to 30% at full amplitude.

The model B7B generates these pulse trains in the following manner. (Refer to Fig. A for time relations of the various pulses.)

The oscillator section creates a continuous train of timing pulses to establish the repetition rate of the output pulse. These timing pulses are used to start delay circuitry to produce what we shall call a start pulse. The start pulse occurs at the end of a time predetermined by the pulse delay controls. The start pulse is used to form the leading edge of the output pulse and to start another delay circuit which produces a second pulse called the stop pulse. This stop pulse occurs at the end of a time predetermined by the setting of the pulse width controls and is used to form the trailing edge of the output pulse. A clamp tube, which is cut off at the time the start pulse occurs, and back on again when the stop pulse occurs, creates what is used as a fill-in pulse between the start and stop pulses. The basic output pulse is therefore created by turning the main pulse on with the start pulse, keeping it on with the fill-in pulse, and turning it off with the stop pulse.




FIG. A TIMING DIAGRAM

The pulse forming circuitry then amplifies the power of this pulse and presents it through suitable attenuation and polarity determining circuitry as the main output pulse.

SPECIFICATIONS

The following are the design specifications of the model B7B pulse generator. The instrument will, in most cases, exhibit properties which are superior to the specifications.


Supplementary circuitry furnishes a synchronizing pulse from the oscillator section for use in synchronizing additional instrumentation with the main output pulse of the generator, a means of triggering the generator from a external source so that it may be synchronized with other instruments, and a means of varying the rise and fall times of the output pulse for applications requiring a degraded pulse shape.

OSCILLATOR REPETITION RATE

The internal oscillator is continuously variable from 20 cycles per second to 2 megacycles per second in five ranges.

20 cps	-	200 cps
200 cps	-	2 kc
2 kc	-	20 kc
20 kc	-	200 kc
200 kc	-	2 mc

Past experience has indicated confusion concerning the definition of some of the basic terminology used in reference to pulses. Fig. B shows these terms as defined by accepted IRE standard pulse terminology. When used in this manual, these terms are meant to be as defined by this standard.



$\text{REPETITION RATE (PULSES/SEC.)} = 1/\text{PERIOD (SEC./PULSE)}$
 $\text{DUTY FACTOR (\%)} = \text{PULSE WIDTH (SEC.)}/\text{PERIOD (SEC.)} \times 100$
 $\text{OVERSHOOT (\%)} = \text{OVERSHOOT (VOLTS)}/\text{PULSE AMPLITUDE (VOLTS)} \times 100$
 $\text{UNDERSHOOT (\%)} = \text{UNDERSHOOT (VOLTS)}/\text{PULSE AMPLITUDE (VOLTS)} \times 100$
 $\text{DROOP (\%)} = \text{DROOP (VOLTS)}/\text{PULSE AMPLITUDE (VOLTS)} \times 100$

FIG. B DEFINITIONS OF BASIC PULSE TERMINOLOGY

PULSE DELAY

Main pulse delay is continuously variable, with respect to the sync. pulse out, from 0.0 microseconds to 10,000 microseconds in five ranges.

0.0 μ sec.	-	1.0 μ sec.
1.0 μ sec.	-	10 μ sec.
10 μ sec.	-	100 μ sec.
100 μ sec.	-	1,000 μ sec.
1,000 μ sec.	-	10,000 μ sec.

PULSE WIDTH

Main pulse width is continuously variable from 0.05 microseconds to 10,000 microseconds in five ranges.

0.05 μ sec.	-	1.0 μ sec.
1.0 μ sec.	-	10 μ sec.
10 μ sec.	-	100 μ sec.
100 μ sec.	-	1,000 μ sec.
1,000 μ sec.	-	10,000 μ sec.

TRIGGER REQUIRED

To trigger the unit from an external source, the following trigger pulse is required.

AMPLITUDE	20V., minimum.
REPETITION RATE	2 mc, maximum.
RISE TIME	1.0 μ sec. or less.
POLARITY	Positive or negative.

NOTE: At lower repetition rates and/or faster rise times, the instrument triggers with a much lower amplitude pulse. The fast rise time quality of the sync. pulse out allows the model B7B to be triggered from the sync. pulse from another model B7B at all repetition rates.

MAIN PULSE

The following are the specifications of the main output pulse.

AMPLITUDE	50V., minimum, into a 50 Ω load.
POLARITY	Positive or negative, but not simultaneously.
RISE TIME	0.015 microseconds.
FALL TIME	0.015 microseconds.

NOTE: Both rise and fall time may be degraded simultaneously to approximately one (1) microsecond.

SYNC PULSE OUT

The following sync. pulse is available at a front panel connector.

AMPLITUDE	10V., minimum.
WIDTH	0.05 μ sec., minimum.
RISE TIME	0.03 μ sec., maximum.
POLARITY	Positive.

OVERSHOOT AND UNDERSHOOT 5%, maximum, except when pulse is attenuated more than 30db. with the 10db. step attenuator. 30%, maximum, at 50db. down.

DROOP:

0-100 μ sec. wide pulse	Negligible.
100-1,000 μ sec. wide pulse	15%, maximum.
1,000-10,000 μ sec. wide pulse	25%, maximum.
DUTY FACTOR	30%, maximum, at full amplitude.
ATTENUATION	0 to 60db., continuously variable.
OUTPUT IMPEDANCE	50 Ω .

MISCELLANEOUS SPECIFICATIONS

The following are miscellaneous specifications of the instrument.

POWER REQUIRED	115V., 3.26 amps., 50-60 cps, 375 watts.
VENTILATION	Forced air.
DIMENSIONS	8 3/4" X 19 1/2" X 13".
WEIGHT, NET	42 lbs.
WEIGHT, SHIPPING	56 lbs.
ACCESSORIES INCLUDED	One instruction manual.

OPERATING INSTRUCTIONS

Refer to Fig. C for the location of all of the front panel controls described below.

FREQUENCY RANGE SWITCH When operated in the internal oscillator positions rotary switch S110 switches timing capacitors C110 through C119 in the grid circuits of V11 to determine the frequency range of the oscillator. In the external trigger position, the switch applies the external trigger pulse to the grid of the Schmitt trigger tube, V12.

FINE FREQUENCY AND TRIGGER SENSITIVITY CONTROL Potentiometer R115 varies the voltage at the grid of V11 to determine the repetition rate of the oscillator on any of the frequency ranges. During periods of external trigger operation this potentiometer becomes the trigger sensitivity control to determine the triggering level.

EXTERNAL TRIGGER POLARITY SWITCH In the two external trigger positions, positive or negative, depending on the polarity of the input signal, the switch selects the positive pulse from the external trigger tube, V10A, and transfers it through S110 to the input of the Schmitt trigger tube, V12.

DELAY RANGE SWITCH Rotary switch S200 switches timing capacitors C200 through C204 in the grid to ground circuit of V20A to determine the range of pulse delay.




FIG. C FRONT PANEL CONTROLS

FINE DELAY CONTROL Potentiometer R208 varies the cathode to ground resistance of the pulse delay multivibrator, affording continuous delay settings on all delay ranges.

WIDTH RANGE SWITCH Rotary switch S300 switches timing capacitors C300 through C304 in the grid to ground circuit of V30A to determine the range of pulse width.

FINE WIDTH CONTROL Potentiometer R308 varies the cathode to ground resistance of the pulse width multivibrator, affording continuous width settings on all width ranges.

10db. STEP ATTENUATOR Rotary switch S800 controls the amplitude of the output pulse in 10db. steps.

FINE ATTENUATOR CONTROL Potentiometer R531 affords a continuously variable attenuation through each range of the 10db. step attenuator.

POLARITY SWITCH Rotary switch S450 determines the polarity of the output pulse by grounding

various levels of the floating power supply and applying its voltages to the output tubes.

RISE TIME CONTROL Potentiometer R401 varies the resistance in the output tube control grid circuits, affording simultaneous degradation of rise and fall times to approximately one microsecond.

EXTERNAL TRIGGER IN J100 couples an external trigger through C100 to the control grid of the external trigger amplifier, V10A.

SYNC. PULSE OUT J101 takes the synchronizing pulse from the cathode of the sync. pulse cathode follower, V10B.

PILOT LIGHT Lamp DS500 lights when 115V. AC, 50-60 cps, single phase power is applied to the power transformer, T500.

ON-OFF SWITCH Switch S500 applies power to the primary winding of the power transformer, T500.

FUSE 4 ampere "slo-blo" fuse F500 protects the pulse generator from overloads.

DUTY CYCLE LIMITING INDICATOR Lamp DS530 lights when the 30% duty factor limitation is exceeded. This lamp, when lit, is a warning to the operator that the amplitude of the output pulse is being automatically reduced.

MAIN PULSE OUT Coaxial connector J800 takes the main pulse from the output of the 10db. step attenuator.

PRELIMINARY INSTRUCTIONS

VENTILATION The model B7B pulse generator is cooled by forced air. It is imperative that both ends of the instrument be kept free of obstructions at all times in order to insure adequate air flow.

It is inadvisable to operate the instrument for appreciable lengths of time with the dust covers removed. These covers not only help to keep the instrument free from dust and other foreign matter, but also properly direct the flow of air through the instrument. Therefore, if the end covers are removed and the instrument mounted in a rack, the dust cover sections must be replaced before rack mounting.

DUTY FACTOR LIMITATION The dissipation limitations of the 6DQ5 power amplifier tubes limit the duty factor of the model B7B pulse generator to 30%, i.e., at full pulse amplitude, the pulse width must never equal greater than 30% of the pulse to pulse spacing. Operation up to approximately 70% duty factor is possible with reduced pulse amplitude.

The 30% duty factor limitation is automatically controlled in the model B7B. Should the duty factor limitation be exceeded, the model B7B automatically reduces the amplitude of the output pulse to such a level that the ratings of the output tubes are not exceeded. When the duty cycle limiter is in operation, the duty cycle lamp on the front panel lights, warning the operator of the reduced pulse amplitude condition.

FIRST TIME OPERATION The following procedure is recommended for putting the instrument into operation for the first time.

1. Turn the power switch to "OFF" and connect the line cord to a source of 115V., 50-60 cps power.
2. Set the instrument controls as follows:

a. Frequency Range	200 kc
b. Frequency	100 kc
c. Delay Range	1 μ sec.
d. Delay	0 μ sec.
e. Width Range	10 μ sec.
f. Width	1 μ sec.
g. 10db. Step Attenuator	0 db.
h. Fine Attenuator	0 db.
i. Polarity	"+"
j. Rise Time	clockwise

3. Connect a synchroscope as follows:

- | | |
|------------------------|---|
| a. Sweep | 1 μ sec./cm |
| b. Vertical Deflection | 20 V./cm |
| c. Trigger | External from the sync. out connector on the model B7B front panel. |

4. Connect a ground strap from one of the model B7B ground binding posts to a ground binding post on the synchroscope.
5. Connect a 50 Ω resistive load between the pulse out connector and ground. The output impedance of the model B7B is 50 Ω and it is imperative that it be properly terminated if the true output waveform is to be observed.
6. Connect the input probe of the synchroscope across the 50 Ω external load. If the true waveform of the output pulse is to be observed, it is imperative that the synchroscope input probe be properly compensated for viewing step function waveforms by adjusting the compensating capacitor in the probe itself and that the probe ground strap be connected to the instrument ground.
7. Turn the model B7B power switch to "ON" and allow approximately one (1) minute for the instrument to reach operating temperature. Adjust the trigger sensitivity of the synchroscope for a stable trace. The model B7B controls may now be set to any desired values within the 30% duty factor limitation.

MAINTENANCE INSTRUCTIONS

DANGER

The power supplies in this instrument operate at voltages which are dangerous to personnel. Extreme caution must be exercised at all times. Repair or maintenance work should never be attempted unless competent personnel, thoroughly trained in the accepted methods of artificial respiration, are in attendance.

DANGER

The following maintenance suggestions are designed to aid the maintenance technician in scheduling regular preventative as well as cor-

rective maintenance routines. It is important that maintenance routines be performed regularly to obtain maximum life and usefulness from the instrument.

FAN MOTOR The fan motor bearings require oil periodically. Use a good grade of light machine oil and apply only a drop or two every six months.

CLEANING THE INSTRUMENT At regular intervals, any dust that has settled on the interior of the instrument should be removed by means of dry compressed air. AVOID high velocity air streams which might injure the instrument or disturb adjustments. Persistent dirt may be removed with a lint-free cloth and, if necessary, carbon tetrachloride.

Under normal conditions, the silver plated contacts of the rotary switches should not require special attention. In case they become tarnished, the contacts should be cleaned by rotating the switch several times.

INSPECTION A visual inspection for loose or broken wiring, loose hardware, and discolored or deformed components is desirable while the instrument is being cleaned.

SWITCHES Turn the rotary switches while observing the contacts to check contact centering in each index position. Improperly centered contacts may be due to the switch becoming warped or twisted. AVOID pressure on the contacts as they are easily damaged.

CAPACITORS AND RESISTORS Inspect the electrolytic capacitors for leakage of electrolyte. Replace if necessary. The wax coating of the paper tubular capacitors may drip if the instrument has been overheated by operation in a restricted space. This condition usually does not indicate replacement.

Composition resistors should be checked for serious discoloration which would indicate excessive dissipation and, therefore, faulty operation. A moderate amount of discoloration is normal.

RACK MOUNTING The model B7B, as purchased, is a portable instrument. It may, however, be mounted in a rack with other instrumentation by removing the louvered end panels. To remove the end panels, first remove both sections of the dust cover. The six sheet metal screws which hold each louvered end panel to the inner end panels are now accessible. Remove these screws and the two screws which hold each end panel to the front panel. Replace both dust covers on the instrument and it is ready for rack mounting. The dust covers must be put back on the instrument before rack mounting as they not only serve to keep dust and other foreign matter out of the instrument, but also help to properly direct the flow of cooling air through the instrument.

CALIBRATION The model B7B contains several controls for the purposes of calibration, pulse shape adjustment, etc. These controls are preset at the factory and should not require readjustment except due to component aging or when electron tubes are replaced.

When readjustment of these controls becomes necessary, the instrument should be allowed to operate for one hour prior to adjustment in order that all components may reach their normal operating temperatures and the instrument has reached maximum stability.

The calibration and checkout chart shown on the following page is patterned after the checkout procedure used at the factory. The chart is intended as a calibration aid only and presupposes that the instrument is in proper working order, except for calibration. It should be noted that there is some interaction between many of the controls. Therefore, it is recommended that the complete calibration and check procedure, working from top to bottom of the chart, be performed at one time on a periodic basis rather than spot adjustments to one circuit which could conceivably have adverse effect on another. Note that an asterisk (*) in any one column indicates that it does not matter which position that control is in for that particular check.

All of the controls used for calibration and adjustment are called out by schematic symbol number on the chassis or circuit board on which they are located, with the following exceptions:

C118 is mounted on the repetition rate switch.

C204 is mounted on the delay switch.

C304 is mounted on the width switch.

R602 is adjustable through the access hole at the rear of the instrument.

TROUBLE SHOOTING It is of extreme importance that the operation, theory, and physical location of components be thoroughly understood before any repair of the instrument is undertaken. A careful study of the circuit descriptions and the schematic diagram will, in most instances, indicate the cause for a particular difficulty in a much shorter time than will a blind point to point check of the entire instrument. It is also suggested that whenever an operational difficulty is encountered, a recheck of the setting and adjustment of the operational controls will often times reveal that a control has been inadvertently set in the wrong position and that this is the cause of the difficulty.

ELECTRON TUBE FAILURE A major cause of equipment failure is weak or inoperative electron tubes. When a system failure has been traced to a particular circuit, it will be found expedient to test the electron tubes in that circuit, replacing all weak or inoperative ones, before a more detailed examination of the circuit is un-

MODEL B7B DIAL SETTINGS										OSCILLOSCOPE SETTINGS		OBSERVE	ADJUST	REMARKS
TO CHECK OR CALIBRATE		REP. RATE		DELAY		WIDTH		ATTENUATOR		POLARITY				
		RANGE	VERNIER	RANGE	VERNIER	RANGE	VERNIER	STOP	VERNIER	OUTPUT	TRIGGER		VERTICAL	HORIZONTAL
PULSE RATE	HIGH END	20K-200K	20	1	1	10	5	0	0W	0	+	0W	20V/cm	0.1milli/sec/cm
	LOW END	20K-200K	2	1	1	10%	5	0	0W	0	+	0W	20V/cm	1 milli/sec/cm
		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	0.1milli/sec/cm
		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	0.1milli/sec/cm
PULSE WIDTH	POSITIVE	EXT. TRIG.	SEE REMARKS	1	MIN	1	MIN	0	0W	0	+	0W	20V/cm	SEE REMARKS
	NEGATIVE	EXT. TRIG.	SEE REMARKS	1	MIN	1	MIN	0	0W	0	-	0W	20V/cm	SEE REMARKS
		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
PULSE DELAY		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
PULSE WIDTH		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
PULSE SHAPE		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
ATTENUATOR		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
POLARITY		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS
		20K-200K	20	1	1	10%	5	0	0W	0	+	0W	20V/cm	SEE REMARKS

ALL OUTPUT PULSES CHARACTERISTICS SHOULD BE MONITORED WITH THE POLARITY SWITCH IN THE "A" POSITION.

dertaken. A HICKOCK #539A Tube Checker has been found very satisfactory in detecting electron tubes with low transconductance.

ISOLATION OF THE DEFECTIVE CIRCUIT The following trouble shooting procedure is designed to isolate the trouble to one particular circuit.

Complete failure of the instrument to operate indicates a power source difficulty. Check the source of power and make certain that the power cord plug is firmly in place. Check the fuse on the instrument front panel. A blown fuse indicates an overload condition within the instrument. Blown fuses should not be indiscriminately replaced without first ascertaining the cause of overload, as further damage is likely to result.

If power is applied to the instrument but it still fails to operate, a check should be made of the power supply voltages. For this and subsequent checks, it will be necessary to remove the dust covers from the instrument.

It will be necessary to use a synchroscope for further checks. It is important that a synchroscope with a wide band-pass be used as it is impossible to observe many of the fast rise times and narrow pulse widths on an inferior synchroscope. The Tektronix models 517, 541, 543, or 545 have been found satisfactory in observing the waveforms present in the instrument.

If the instrument has no output pulse, check for a sync. pulse at the sync. out jack on the instrument front panel. If there is no sync. pulse, the trouble is in the oscillator section of the instrument. If, however, a sync. pulse is present, synchronize a synchroscope with this pulse and proceed as follows.

Check for a pulse at the input of the attenuator switch, S800. A pulse here isolates the trouble to the switch or its components. If no pulse or a deformed pulse is present, check for a pulse at pins 3 and 6 of V40. If a normal pulse is present at this point, the faulty circuitry is in the output section.

If no pulse is present at the cathodes of V40, the trouble will probably be found in the delay multivibrator or blocking oscillator. If, however, a deformed pulse is present, a study of its shape will be helpful in quickly finding its cause.

If the deformed pulse shows a very slow rise time and normal fall time, the start pulse is missing. Check the start pulse channel. If there are very narrow pulses where the leading and trailing edges of the output pulse would normally be, the clamp circuit is inoperative. If the pulse rises normally and then immediately starts to decay slowly toward zero, the trouble lies in the clamp circuit or the width multivibrator circuit. Finally, if the pulse is normal except for a slow fall time, check the stop pulse channel for faulty operation.

In checking each subsection, it is advisable to start by looking for an output pulse from the section and then work back toward the start of the section. Thus, whenever a normal pulse is found, the trouble is isolated to the stage which immediately follows it.

CIRCUIT DESCRIPTION

OSCILLATOR SECTION The oscillator section consists of the external trigger amplifier, V10A; the free-running multivibrator, V11; the Schmitt trigger, V12; the repetition rate blocking oscillator, V13; and the sync. pulse cathode follower, V10B. V10, V11, V12, and V13 are type 6DJ8 dual triode electron tubes.

The repetition rate of the free-running multivibrator is determined by the action of two front panel controls. The range of the oscillator is determined by the selection of timing capacitors C110 through C119, in the grid circuits of V11, by the oscillator range switch, S110. Fine repetition rate control of the multivibrator, through any range, is determined by varying the fine frequency potentiometer, R115, which varies the voltage to this grid circuit.

The limits of repetition rate for each range are set with the two calibration potentiometers, R111 and R116, which establish the range through which this voltage may vary.

The output, taken from the plate of the multivibrator triggers the Schmitt trigger circuit. The Schmitt trigger circuit shapes the pulse, and sends it to the repetition rate blocking oscillator.

The repetition rate blocking oscillator again shapes the pulse. The basic repetition rate timing pulse is taken from the cathode of this blocking oscillator and is used to trigger the delay multivibrator.

The external trigger amplifier provides a means of triggering the instrument from an external source. The external trigger polarity switch, in either the positive or negative position, depending on the polarity of the input signal, couples the positive pulse from V10A through the repetition rate range switch, S110, to the input grid of the Schmitt trigger. Potentiometer R115 now becomes a trigger sensitivity control to set the triggering level. It should be noted that the repetition rate switch, S110, must be placed in the external trigger position in order to trigger the model B7B from an external source.

The timing pulse taken from the cathode of the repetition rate blocking oscillator is also coupled through a 0.2 μ sec. delay line to the

grid of the sync. pulse cathode follower. The pulse taken from the cathode is brought to the instrument front panel to be used as a synchronizing pulse for use with other instrumentation. Due to the fact that the sync. pulse occurs approximately 0.2 μ sec. after the pulse which triggers the pulse delay circuit, we are able to overcome the inherent delay of the remaining circuitry and can thus produce output pulses which are not delayed in time with respect to the sync. pulse.

DELAY SECTION The delay section consists of the delay multivibrator, V20, and the delay blocking oscillator, V21. V20 is a type 6DJ8 dual triode electron tube and V21 is a type 6BQ7A dual triode electron tube.

The monostable multivibrator, V20, is triggered from its stable state to its quasi-stable state by positive pulses from the oscillator section which are coupled into the grid of V20B and the plate of V20A through diode CR201. The length of time which the multivibrator remains in this quasi-stable state, determined by the timing capacitor in the grid circuit of V20A and the cathode to ground resistance of V20, is the delay time of the circuit. Thus, this circuit determines the time between the oscillator section timing pulse and the start of the main pulse.

The range of delay is determined by the selection of timing capacitors C200 through C204 by the delay range switch, S200. Fine delay control throughout any range is determined by varying the cathode to ground resistance with the fine delay potentiometer, R208.

R200 sets the voltage to which the grid circuit is returned, thus providing calibration for the various ranges.

A pulse, created by the return of the multivibrator to its stable state after this predetermined delay, is coupled from the plate of V20B to trigger the delay blocking oscillator, V21.

The pulse taken from the cathode of the blocking oscillator is known as the "start pulse". This start pulse goes to the amplifiers in the start channel and to the width section where it is used to trigger the width multivibrator.

WIDTH SECTION The pulse width section consists of the width multivibrator, V30. V30 is a type 6DJ8 dual triode electron tube.

The monostable multivibrator, V30, is triggered from its stable state to its quasi-stable state by positive pulses from the delay section which are coupled into the grid of V30B and the plate of V30A through diode CR301. The length of time which the multivibrator remains in this quasi-stable state, determined by the timing capacitor in the grid circuit of V30A and the cathode to ground resistance of V30, is the

delay time of this circuit. Thus, this circuit determined the time between the delay section output pulse which starts the main pulse and the width section output pulse which stops the main pulse.

The range of pulse width, is determined by the selection of timing capacitors C300 through C304 by the width range switch, S300. Fine width control throughout any range is determined by varying the cathode to ground resistance with the fine width potentiometer, R308.

R300 sets the voltage to which the grid circuit is returned, thus providing calibration for the various ranges.

Two outputs are taken from the width multivibrator. The first is the waveform taken from the plate circuit of V30B. This waveform is a negative going pulse equal in time duration to the delay time of the width multivibrator. It is coupled through C310 to the grid of the clamp tube, V35B. The second output, a pulse created by the return of the multivibrator to its stable state after the predetermined delay, is known as the "stop pulse". This stop pulse is coupled into the amplifiers in the stop channel.

START PULSE CHANNEL The start pulse channel consists of three pulse shaping amplifier stages and the leading edge forming tube. V25 and V26 are type 7119 dual triode electron tubes. V27 is a type 6BQ7A dual triode electron tube.

The start channel receives the positive start pulse from the delay section through a 0.02 microsecond delay line, DL210. This delay line delays the start pulse without delaying the stop pulse, thus allowing a minimum output pulse width of 0.05 microseconds. This pulse goes through three pulse transformer coupled amplifier stages; V25A, V25B, and V26. Pulse transformer T260 couples the amplified pulse into the grids of the leading edge forming tube, V27. This tube drives the output pulse cathode follower, in the pulse forming section, to form the leading edge of the output pulse.

STOP PULSE CHANNEL The stop pulse channel consists of three pulse shaping amplifier stages and the trailing edge forming tube. V35A is $\frac{1}{2}$ of a type 6BQ7A dual triode electron tube. V36 and V37 are type 7119 dual triode electron tubes.

The stop channel receives the positive stop pulse from the width section. It is sent through three stages of transformer coupled amplification; V35A, V36A, and V36B, into the grids of the trailing edge forming tube, V37. This tube drives the output pulse cathode follower, in the pulse forming section, to form the trailing edge of the output pulse.

OUTPUT SECTION The output section consists of the clamp tube, V35B; the pulse forming cathode follower, V40; two power amplifier tubes, V45 and V46; the control grid restoration diode, V47A; and the screen grid disconnect diode,

V47B. Electron tube V35B is $\frac{1}{2}$ of a type 6BQ7A dual triode, V40 is a type 7119 dual triode, V45 and V46 are type 6DQ5 power pentodes, and V47 is a type 6DJ8 dual triode.

The clamp tube receives its input from the plate circuit of V30B in the pulse width section. During the period between output pulses, it conducts fully, holding the output at the zero level. Between the start and stop pulses it is completely cut off by the signal from the width multivibrator and holds the output pulse at full amplitude.

The grids of the pulse forming cathode follower are driven positive by the leading edge forming tube, held there by the clamp tube, and driven back to their original level by the trailing edge forming tube. From the cathodes of this tube, we take the fully shaped output pulse. This pulse is coupled through the rise time control circuitry to the control grids of the power amplifiers.

The power amplifiers, connected in parallel, act as a cathode follower for a positive pulse out, and as an inverting amplifier for a negative pulse out. This is accomplished by the action of the polarity switch, S450, which switches the floating power supply voltages to the output power amplifiers as well as coupling the output pulse to the attenuator.

Triode V47A, connected as a diode, provides restoration at the control grids of the output tubes. The restoration level is adjusted by potentiometer R473. V47B, as connected, acts as the screen grid disconnect diode for the output amplifiers.

Finally, the output pulse is sent to the step attenuator, consisting of five 10db. constant impedance T-sections, and to the pulse output jack on the instrument front panel.

POWER SUPPLY SECTION The power supply section contains the power transformer, T500; V50, a type 0A2 voltage regulator tube; V51, a type 6AS7GA dual triode electron tube; V52, a type 12AX7 dual triode electron tube; V53, a type 6U8 triode-pentode electron tube, and their associated circuitry which includes two controls for varying the amplitude of the output pulse.

The power supply section furnishes five unregulated DC voltages (+250V., -4V., -8V., -18V., and -24V.), and three regulated voltages (+150V., -150V., and a positive variable voltage) from its ground reference supplies. From its floating supply it furnishes 150V. above and below a zero reference. It also furnishes filament power for all of the electron tubes in the unit.

The +150V. supply is regulated by the action of V51A and V52A. The -150V. supply is regulated by the action of the voltage regulator tube, V50.

The positive variable voltage, used in two places; as plate supply for the last stage of

start pulse amplification and as plate supply for the clamp tube; furnishes a means of varying the amplitude of the output pulse. This supply is regulated by the action of V51B and V52B. Its reference, however, is set by V53B.

This reference may be varied in two ways. First, it may be varied by varying the fine attenuator, R531. Secondly, it may be varied by the action of the duty cycle limiting control consisting of the circuitry of T600 and V53A.

Transformer T600 senses the ripple voltage in the zero leg of the floating supply. This ripple voltage increases as the output power amplifiers draw more current. The bias on the control grid of V53A is set at such a level by potentiometer R602 that the ripple voltage will take control of the tube at the point where the power amplifiers are drawing rated current and change the reference to lower the variable supply voltage. Thus, the output tubes are never allowed to exceed their dissipation ratings even if the duty factor limitation is inadvertently exceeded. At the time the variable voltage starts to decrease due to duty cycle limiting, the front panel lamp DS530, lights to warn the operator that the amplitude of the output pulse is being automatically reduced.

CIRCUIT THEORY

This section of the manual contains explanations of several basic circuits which are used in the model B7B. Inasmuch as the technician may not be totally familiar with high repetition rate pulse handling circuitry, it is felt that the inclusion of this section in the manual will lend to a more thorough understanding of the instrument.

FREE-RUNNING MULTIVIBRATOR Fig. D is a simplified circuit of a free-running multivibrator similar to that used in the oscillator section of the model B7B.

Arbitrarily assume that at any specified instant, triode section V1 is conducting fully and triode section V2 is non-conducting because the potential at its control grid is below the cut-off potential of the tube. At this instant, the plate voltage of V1 is lowered due to the current flow through V1 and R1. C2 discharges to this voltage, holding V2 cut off.

After a time determined by the discharge time of C2 through R4, the voltage potential on the grid of V2 reaches the cut-in potential of the tube. V2 starts to conduct and its plate potential drops. This drop is immediately felt at the grid of V1 across C1, driving it to cut-off. Its plate potential rises sharply and capacitor C2 charges to the new voltage, further aiding

in the conduction of V2. After the initial change, V2 steadies to a low plate voltage and C1 discharges to the cut-in potential of V1 and the cycle starts over again.




FIG. D FREE-RUNNING MULTIVIBRATOR

In summary, the operation of this circuit consists of periods of time when one tube conducts a high current while the other tube is cut off, followed by an extremely rapid change to the other tube conducting and the first tube cut off.

The repetition rate of the circuit is determined by the time constants of C1-R3 and C2-R4 and the voltage to which they are returned.

In the model B7B the range of the repetition rate of the oscillator is changed by changing the values of C1 and C2 in decade steps and the repetition rate is made continuously variable for each range by varying the level of the grid return voltage.

MONOSTABLE MULTIVIBRATOR Fig. E shows a simplified circuit of a monostable multivibrator similar to those used in the pulse delay and pulse width sections of the model B7B.

The multivibrator has one stable state and one quasi-stable state. That is, one tube section is capable of remaining in the conducting state indefinitely while the other does not have this capability. In this type of multivibrator it is necessary to trigger the circuit from its stable state to its quasi-stable state with trigger pulses from an external source. Then, the circuit will automatically return to its stable state after a certain length of time. Therefore, in operation, one triode section is triggered from non-conduction to conduction with an applied trigger. It remains in this condition for a predetermined length of time and then returns abruptly to the non-conducting state to await another trigger. Thus, we are able to generate a pulse, at a predetermined time after

a given input pulse, by abruptly changing a tube section from conduction to non-conduction. Or, essentially, we have introduced a delay into the system.

Assume that the circuit is in its stable state. V1 is conducting, its grid clamped to its cathode. If R2 is made quite large, the full conduction current through V1 and thus through R6 is small and the grid is clamped near zero potential. The plate of V1, however, is at quite a low potential due to the current through the large R2. V2 is not conducting, its grid held below cut-off by the divider formed by R3, R4, and R7 between the low positive plate potential of V1 and -150 volts.

Now, at some time, a positive timing pulse arrives at the junction of the C2-R3, C3-R4 combination through diode CR1. This pulse is felt sharply across C2 and C3 at the plate of V1 and the grid of V2. V1 starts to cut off. V2 starts conducting. If R5 is small compared to R2, V2 will conduct much more heavily than V1




FIG. E MONOSTABLE MULTIVIBRATOR

was conducting. The drop across R6 becomes greater due to this higher current through V2, thus the cathodes raise to a higher potential. This holds V1 off completely. The plate of V1,

now at a higher potential, keeps the grid of V2 above its cut-off potential by the same divider network mentioned above. Thus, in a very short time, a trigger pulse has changed the state of the multivibrator from that of V1 conducting a small amount and V2 cut off, to one of V1 cut off and V2 conducting quite heavily.




FIG. F MONOSTABLE BLOCKING OSCILLATOR

As soon as V1 is cut off by raising its cathode potential several volts with respect to its grid potential, C1 starts to charge through R1 toward the B+ potential. After a time, predetermined by the R1-C1 combination, the grid of V1 will reach cut-in potential and V1 will again start to conduct. The plate of V1 drops. This drop is felt at the grid of V2 through C2 and C3, immediately cutting off V2. The drop which cuts V2 off also drops the cathode potentials, which aids the conduction of V1. C1 discharges rapidly through the low grid to cathode resistance of V1, and the circuit has returned to its original stable state. At the transition point of V2 conducting to non-conducting, the plate waveform of V2 goes sharply positive. This waveform is taken as the output. Thus, we have produced a pulse, delayed from the original trigger pulse, by a time predetermined by R1-C1.

In the model B7B the range of delay of the pulse delay and pulse width multivibrators is changed by changing the value of C1 in decade steps. Delay and width are made continuously variable through any range by varying R6, which varies the cathode potential in the quasi-stable state, thus determining the potential which the grid must reach to cut V1 on and return the multivibrator to its stable state.

BLOCKING OSCILLATOR Fig. F shows a typical blocking oscillator circuit such as is used in the model B7B oscillator and pulse delay sections.

This blocking oscillator is a so-called monostable or driven type. That is, it is not free-running, but requires a trigger from an external source to excite it. It produces a high powered, extremely sharp, narrow pulse which is essentially independent of the shape or degradation of the pulse which triggers it.

V1 serves to amplify the input trigger and to eliminate the possibility of a reaction by the blocking oscillator back on the trigger pulse source.

In the quiescent condition, both sections of the tube are biased below cut-off. A positive trigger is coupled through C1 to the amplifier tube, V1, which inverts and amplifies it. Pulse transformer T1 inverts and applies this waveform to the grid of V2, the blocking oscillator tube. V2 conducts causing a drop in its plate voltage. The drop in plate voltage in turn causes an increase in grid voltage, which results in a further decrease in plate voltage. Due to the AC loop gain of the circuit being greater than unity, regeneration occurs. The plate drives abruptly downward and the grid abruptly upward. This action continues until such time as the loop gain drops below unity, due to the non-linearity of the tube.

The plate and grid cannot remain at the values attained by the regenerative action described above because of the low frequency characteristics of the transformer. The grid starts to drop due to its finite magnetizing inductance. When the grid voltage has dropped far enough that the loop gain once again equals unity, a regenerative action once again occurs in the direction to turn the tube off.

An overshoot occurs at the plate and grid of the tube. At the conclusion of the pulse there is still a current flowing in the magnetizing inductance of the transformer. Since this current cannot change instantaneously, it continues to flow through the effective capacitance of the transformer after the tube current has dropped to zero, causing this overshoot.

The pulse width and rise time are dependent almost entirely on the design of the transformer. The pulse transformers used in the model B7B blocking oscillators are specifically designed to produce extremely narrow, fast rise time pulses.

In the oscillator and pulse width sections of the model B7B, blocking oscillators such as described above are used. In both of these cases, a positive pulse is taken from the cathode as the output pulse.

SCHMITT TRIGGER Figure "G" shows a typical Schmitt Trigger circuit such as is used in the Model B7B Oscillator section.

The Schmitt Trigger is a mono-stable circuit, that is, it is not free running but requires a trigger from an external source to excite it. This circuit produces an extremely sharp pulse which is essentially independent of the amplitude and waveform of the pulse which triggers it.

In the quiescent condition, V-2 is conducting, V-1 is not conducting, its grid held below cut-off by the divider network formed by R-4 and R-5 between the cathodes of V-1 and V-2 and

ground. A positive trigger is coupled through C-1 to the grid of V-1 causing the tube to conduct. For an instant, the voltage across the cathode resistors increases driving the grid of V-2 towards cut-off. This, in addition with the drop-in plate voltage of V-1, causes a rapid change in V-2 from conducting to a cut-off condition. V-2 will remain cut-off until the input signal has decreased to the cut-off value of V-1. As soon as V-1 is cut off by the changing input signal, the plate voltage of V-1 will rise, causing the voltage on the grid of V-2 to rise, and V-2 conducts.

Thus, in a short time the circuit has been triggered between its two stable states by a trigger pulse whose amplitude exceeds a definite positive value and changes to a definite less positive value.




FIG. G SCHMITT TRIGGER

PARTS LIST

NOTE: Capacitors marked with an asterisk (*) are bridged and grouped to $\pm 1\%$ accuracy at our factory. If it becomes necessary to replace any one of these capacitors, all of the capacitors on the switch should be replaced with a set obtained through our Sales Department.

ABBREVIATIONS

cer	ceramic	k	kilohm of 10^3 ohms	prec	precision
comp	composition	m	milli or 10^{-3}	PT	paper tubular
EMC	electrolytic, metal cased	meg	megohm or 10^6 ohms	SM	silvered mica
EMT	electrolytic, metal tubular	MF	metal film	V	working volts, DC
f	farad	μ	micro or 10^{-6}	var	variable
GMV	guaranteed minimum value	$\mu\mu$	micromicro or 10^{-12}	W	watt
h	henry	Ω	ohm	WW	wire wound

CAPACITORS											
						C130	100 μ f	fixed	cer	500V	$\pm 10\%$
						C131	.01 μ f	fixed	cer	500V	GMV
						C132	.01 μ f	fixed	cer	500V	GMV
C100	.01 μ f	fixed	cer	500V	GMV	C200*	.47 μ f	fixed	mylar	150V	$\pm 5\%$
C101	.01 μ f	fixed	cer	500V	GMV	C201*	.047 μ f	fixed	mylar	150V	$\pm 5\%$
C102	.01 μ f	fixed	cer	500V	GMV	C202*	4700 μ f	fixed	SM	500V	$\pm 5\%$
C103	.01 μ f	fixed	cer	500V	GMV	C203*	470 μ f	fixed	SM	500V	$\pm 5\%$
C104	.01 μ f	fixed	cer	500V	GMV	C204	5-80 μ f	var	mica	175V	
C105	.01 μ f	fixed	cer	500V	GMV	C205	.01 μ f	fixed	cer	500V	GMV
						C206	100 μ f	fixed	SM	500V	$\pm 5\%$
C110*	.47 μ f	fixed	mylar	150V	$\pm 5\%$	C207	100 μ f	fixed	SM	500V	$\pm 5\%$
C111*	.47 μ f	fixed	mylar	150V	$\pm 5\%$	C208	100 μ f	fixed	cer	500V	$\pm 10\%$
C112*	.047 μ f	fixed	mylar	150V	$\pm 5\%$	C209	.01 μ f	fixed	cer	500V	GMV
C113*	.047 μ f	fixed	mylar	150V	$\pm 5\%$						
C114*	4700 μ f	fixed	SM	500V	$\pm 5\%$	C210	100 μ f	fixed	cer	500V	$\pm 10\%$
C115*	4700 μ f	fixed	SM	500V	$\pm 5\%$	C211	.01 μ f	fixed	cer	500V	GMV
C116*	470 μ f	fixed	SM	500V	$\pm 5\%$	C212	.01 μ f	fixed	cer	500V	GMV
C117*	470 μ f	fixed	SM	500V	$\pm 5\%$	C213	.01 μ f	fixed	cer	500V	GMV
C118	5-80 μ f	var	mica	175V							
C119	47 μ f	fixed	SM	500V	$\pm 5\%$						
C120	100 μ f	fixed	cer	500V	$\pm 10\%$	C250	.01 μ f	fixed	cer	500V	GMV
C121	5 μ f	fixed	SM	500V	$\pm 5\%$						
C122	100 μ f	fixed	cer	500V	$\pm 10\%$	C260	1.5-7 μ f	var	cer	500V	
C123	.01 μ f	fixed	cer	500V	GMV	C261	.01 μ f	fixed	cer	500V	GMV

C300*	.47 μ f	fixed	mylar	150V	$\pm 5\%$
C301*	.047 μ f	fixed	mylar	150V	$\pm 5\%$
C302*	4700 μ f	fixed	SM	500V	$\pm 5\%$
C303*	470 μ f	fixed	SM	500V	$\pm 5\%$
C304	4-80 μ f	var	mica	175V	
C306	100 μ f	fixed	SM	500V	$\pm 5\%$
C307	100 μ f	fixed	SM	500V	$\pm 5\%$
C308	100 μ f	fixed	cer	500V	$\pm 10\%$
C309	2 μ f	fixed	EMT	450V	-10+50%
C310	.25 μ f	fixed	MP	200V	$\pm 20\%$
C311	.01 μ f	fixed	cer	500V	GMV
C352	.01 μ f	fixed	cer	500V	GMV
C353	.01 μ f	fixed	cer	500V	GMV
C354	4-30 μ f	var	cer	500V	
C360	4-30 μ f	var	cer	500V	
C361	.01 μ f	fixed	cer	500V	GMV
C362	.01 μ f	fixed	cer	500V	GMV
C363	.01 μ f	fixed	cer	500V	GMV
C400	.5 μ f	fixed	MP	600V	$\pm 20\%$
C401	.01 μ f	fixed	cer	500V	GMV
C402	.01 μ f	fixed	cer	500V	GMV
C403	.01 μ f	fixed	cer	500V	GMV
C404	.01 μ f	fixed	cer	500V	GMV
C405	2 μ f	fixed	EMT	450V	-10+50%
C450	20 μ f	fixed	EMT	250V	-10+50%
C451	.01 μ f	fixed	cer	500V	GMV
C452	33 μ f	fixed	SM	500V	$\pm 5\%$
C453	22 μ f	fixed	SM	500V	$\pm 5\%$
C460	20 μ f	fixed	EMT	250V	-10+50%
C461	.01 μ f	fixed	cer	500V	GMV
C462	33 μ f	fixed	SM	500V	$\pm 5\%$
C470	.25 μ f	fixed	MP	200V	$\pm 20\%$
C471	.01 μ f	fixed	cer	500V	GMV
C472	9-180 μ f	var	mica	175V	
C473	.01 μ f	fixed	cer	500V	GMV
C474	.25 μ f	fixed	MP	200V	$\pm 20\%$
C500	80-80 μ f	fixed	EMC	350V	-10+50%
C501	80-80 μ f	fixed	EMC	350V	-10+50%
C502	80-80 μ f	fixed	EMC	350V	-10+50%
C503	.1 μ f	fixed	PT	400V	$\pm 20\%$
C520	.1 μ f	fixed	PT	400V	$\pm 20\%$
C521	2 μ f	fixed	EMT	450V	-10+50%
C522	.1 μ f	fixed	PT	400V	$\pm 20\%$
C523	2 μ f	fixed	EMT	450V	-10+50%
C530	.1 μ f	fixed	PT	400V	$\pm 20\%$
C531	.1 μ f	fixed	PT	400V	$\pm 20\%$
C600	50 μ f	fixed	EMT	25V	-10+100%
C601	200-200 μ f	fixed	EMC	250V	-10+50%
C602	200-200 μ f	fixed	EMC	250V	-10+50%
C603	200-200 μ f	fixed	EMC	250V	-10+50%
C604	200-200 μ f	fixed	EMC	250V	-10+50%

C700	1500 μ f	fixed	EMC	50V	-10+50%
C801	2 μ f	fixed	MP	200V	$\pm 20\%$
~~C802~~	~~.25 μf~~	~~fixed~~	~~MP~~	~~200V~~	~~$\pm 20\%$~~
C804	2 μ f	fixed	MP	200V	$\pm 20\%$
C805	22 μ f	fixed	cer	1KV	$\pm 20\%$

CHOKES

L120	75 μ h	fixed		$\pm 10\%$
L200	25 μ h	fixed		$\pm 10\%$
L300	25 μ h	fixed		$\pm 10\%$

CONNECTORS

J100		Nylon Binding Post
J101		Nylon Binding Post

J800	Type SO-239
------	-------------

DELAY LINES

DL100	.2 μ second	fixed
DL210	.02 μ second	fixed

DIODES

CR120	(Hughes Aircraft Co. ONLY)	Type 1N116
CR130		Type 1N34A
CR200		Type 1N34A
CR201	(Hughes Aircraft Co. ONLY)	Type 1N116
CR210		Type 1N34A
CR250		Type 1N774
CR251		Type 1N774
CR300		Type 1N34A
CR301	(Hughes Aircraft Co. ONLY)	Type 1N116

CR350	Type 1N774			FUSE					
CR360	Type 1N774			F500	4 amperes		Slo-blo		
CR361	Type 1N774			LAMPS					
CR500	Rectifier, Silicon	200ma	360 PIV	DS500 DS530	#47 NE-51				
CR501	Rectifier, Silicon	200ma	360 PIV						
CR502	Rectifier, Silicon	200ma	360 PIV						
CR503	Rectifier, Silicon	200ma	360 PIV						
CR504	Rectifier, Silicon	200ma	360 PIV						
CR505	Rectifier, Silicon	200ma	360 PIV	RESISTORS					
CR530	Rectifier, Silicon	200ma	360 PIV	R100	150k	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
CR600	Rectifier, Silicon	500ma	400 PIV	R101	1k	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
CR601	Rectifier, Silicon	500ma	400 PIV	R102	10k	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
CR602	Rectifier, Silicon	500ma	400 PIV	R103	1k	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
CR603	Rectifier, Silicon	500ma	400 PIV	R104	1k	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
CR604	Rectifier, Silicon	200ma	360 PIV	R105	680 Ω	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
CR700	Rectifier, Silicon	200ma	360 PIV	R110	1k	fixed	comp	1W	$\pm 10\%$
CR701	Rectifier, Silicon	200ma	360 PIV	R111	10k	var	comp	2W	$\pm 20\%$
~~VR705~~	~~Type 1N2986RA~~			R112	1k	fixed	comp	1W	$\pm 10\%$
				R113	75k	fixed	comp	$\frac{1}{8}W$	$\pm 5\%$
				R114	75k	fixed	comp	$\frac{1}{8}W$	$\pm 5\%$
				R115	10k	var	comp	2W	$\pm 20\%$
				R116	5k	var	comp	1W	$\pm 20\%$
				R117	4.7k	fixed	comp	2W	$\pm 10\%$
				R120	6.8k	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
				R121	470 Ω	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
				R122	150k	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
				R123	1meg	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
V10	Type 6DJ8			R124	1.2k	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
V11	Type 6DJ8			R125	6.8k	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
V12	Type 6DJ8			R126	68k	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
V13	Type 6DJ8			R127	39k	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
V20	Type 6DJ8			R128	3.3meg	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
V21	Type 6BQ7A			R130	470 Ω	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
V25	Type 7119			R131	1k	fixed	comp	1W	$\pm 10\%$
V26	Type 7119			R132	1k	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
V27	Type 6BQ7A			R200	100k	var	comp	1W	$\pm 20\%$
V30	Type 6DJ8			R201	100k	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
V35	Type 6BQ7A			R202	47 Ω	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
V36	Type 7119			R203	470 Ω	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
V37	Type 7119			R204	100k	fixed	prec	$\frac{1}{8}W$	$\pm 1\%$
V40	Type 7119			R205	27k	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
V45	Type 6DQ5			R206	12k	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
V46	Type 6DQ5			R207	220 Ω	fixed	comp	2W	$\pm 10\%$
V47	Type 6DJ8			R208	500 Ω	var	comp	2W	$\pm 20\%$
V50	Type OA2			R209	300k	fixed	comp	$\frac{1}{8}W$	$\pm 5\%$
V51	Type 6AS7GA			R210	470 Ω	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
V52	Type 12AX7			R211	3.3k	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
V53	Type 6U8A			R212	470 Ω	fixed	comp	2W	$\pm 10\%$
				R250	1k	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
				R251	150 Ω	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
				R252	330 Ω	fixed	comp	$\frac{1}{8}W$	$\pm 10\%$
				R260	1k	fixed	comp	2W	$\pm 10\%$
				R261	1k	fixed	comp	2W	$\pm 10\%$

R300	100k	var	comp	1W	±20%
R301	100k	fixed	comp	$\frac{1}{2}$ W	±10%
R302	47Ω	fixed	comp	$\frac{1}{2}$ W	±10%
R303	470Ω	fixed	comp	$\frac{1}{2}$ W	±10%
R304	100k	fixed	prec	$\frac{1}{2}$ W	± 1%
R305	27k	fixed	comp	$\frac{1}{2}$ W	±10%
R306	12k	fixed	comp	$\frac{1}{2}$ W	±10%
R307	470Ω	fixed	comp	2W	±10%
R308	500Ω	var	comp	2W	±20%
R309	300k	fixed	comp	$\frac{1}{2}$ W	± 5%

R350	~~39k~~ 470	fixed	comp	$\frac{1}{2}$ W	±10%
R351	3.3k	fixed	comp	$\frac{1}{2}$ W	±10%
R352	330Ω	fixed	comp	$\frac{1}{2}$ W	±10%
R353	250k	var	comp	2W	±30%
R354	50k	var	comp	2W	±30%
R355	150k	fixed	comp	$\frac{1}{2}$ W	±10%
R356	68k	fixed	comp	2W	±10%
R357	27k	fixed	comp	$\frac{1}{2}$ W	±10%

R360	330Ω	fixed	comp	$\frac{1}{2}$ W	±10%
R361	330Ω	fixed	comp	$\frac{1}{2}$ W	±10%

R400	22k	fixed	comp	2W	±10%
R401	10k	var	comp	2W	±30%
R402	3.3k	fixed	comp	2W	±10%

R450	10Ω	fixed	comp	2W	±10%
------	-----	-------	------	----	------

R452	47Ω	fixed	comp	$\frac{1}{2}$ W	±10%
R453	100Ω	fixed	comp	$\frac{1}{2}$ W	±10%

R460	10Ω	fixed	comp	2W	±10%
------	-----	-------	------	----	------

R462	47Ω	fixed	comp	$\frac{1}{2}$ W	±10%
------	-----	-------	------	-----------------	------

R470	1meg	fixed	comp	$\frac{1}{2}$ W	±10%
R471	1.5k	fixed	comp	$\frac{1}{2}$ W	±10%
R472	4.7k	fixed	comp	2W	±10%
R473	5k	var	comp	2W	±30%
R474	3.3k	fixed	comp	2W	±10%
R475	100Ω	fixed	comp	$\frac{1}{2}$ W	±10%

R500	100k	fixed	comp	$\frac{1}{2}$ W	±10%
R501	3k	fixed	WW	10W	±10%
R502	150k	fixed	comp	1W	±10%

R510	10Ω	fixed	comp	$\frac{1}{2}$ W	±10%
R511	~~732~~ 73k	fixed	prec	$\frac{1}{2}$ W	± 1%
R512	~~681~~ 68k	fixed	prec	$\frac{1}{2}$ W	± 1%
R513	10Ω	fixed	comp	$\frac{1}{2}$ W	±10%
R514	220k	fixed	comp	$\frac{1}{2}$ W	± 5%
R515	150k	fixed	comp	$\frac{1}{2}$ W	± 5%
R516	1500Ω	fixed	WW	25W	±10%

R520	220k	fixed	comp	$\frac{1}{2}$ W	±10%
R521	470k	fixed	comp	$\frac{1}{2}$ W	±10%
R522	22k	fixed	comp	2W	±10%

R530	270k	fixed	comp	$\frac{1}{2}$ W	± 5%
R531	250k	var	comp	2W	±20%
R532	680k	fixed	comp	$\frac{1}{2}$ W	±10%
R533	120k	fixed	comp	$\frac{1}{2}$ W	±10%
R534	100k	fixed	comp	$\frac{1}{2}$ W	±10%
R535	6.8k	fixed	comp	2W	±10%
R536	6.8k	fixed	comp	2W	±10%

R600	0.75Ω	fixed	WW	5W	± 5%
R601	3.3meg	fixed	comp	$\frac{1}{2}$ W	±10%
R602	50k	var	comp	1W	±30%
R603	15k	fixed	comp	$\frac{1}{2}$ W	±10%
R604	100k	fixed	comp	$\frac{1}{2}$ W	±10%
R605	100k	fixed	comp	$\frac{1}{2}$ W	±10%

R700	~~47~~ 100Ω	fixed	comp	~~1~~ W	± 5%
R701	160Ω	fixed	comp	2W	± 5%
R702	~~33~~ 68Ω	fixed	comp	1W	± 5%
R703	~~33~~ 68Ω	fixed	comp	1W	± 5%
R704	~~33~~ 68Ω	fixed	comp	~~1~~ W	±10%
R705	~~160~~ 160Ω	"	"	~~2~~ W	
R800	270Ω	fixed	MF	8W	± 5%
R801	270Ω	fixed	MF	8W	± 5%
R802	270Ω	fixed	MF	8W	± 5%
R803	75Ω	fixed	MF	6W	± 5%
R804	75Ω	fixed	MF	6W	± 5%
R805	75Ω	fixed	MF	6W	± 5%
R806	82k	fixed	comp	$\frac{1}{2}$ W	±10%
R807	82k	fixed	comp	$\frac{1}{2}$ W	±10%
R810	2ea 52Ω	fixed	MF	6W	± 5%
R811	26Ω	fixed	MF	6W	± 5%
R812	2ea 70Ω	fixed	MF	6W	± 5%

R820	26Ω	fixed	MF	4W	± 5%
R821	26Ω	fixed	MF	4W	± 5%
R822	35Ω	fixed	MF	4W	± 5%

R830	27Ω	fixed	comp	$\frac{1}{2}$ W	± 5%
R831	27Ω	fixed	comp	$\frac{1}{2}$ W	± 5%
R832	36Ω	fixed	comp	$\frac{1}{2}$ W	± 5%

R840	27Ω	fixed	comp	$\frac{1}{2}$ W	± 5%
R841	27Ω	fixed	comp	$\frac{1}{2}$ W	± 5%
R842	36Ω	fixed	comp	$\frac{1}{2}$ W	± 5%

R850	27Ω	fixed	comp	$\frac{1}{2}$ W	± 5%
R851	27Ω	fixed	comp	$\frac{1}{2}$ W	± 5%
R852	36Ω	fixed	comp	$\frac{1}{2}$ W	± 5%

SWITCHES

S100	SPDT	EXT. TRIG. POL. TOGGL	
S110	B7B-B-519		RUTHERFOR
S200	B7B-B-520		RUTHERFOR
S300	B7B-B-520		RUTHERFOR

S450	B7B-B-522	RUTHERFORD	T250 T251	B7-502 B7-504	RUTHERFORD RUTHERFORD
S500	SPST	"ON-OFF" TOGGLE	T260	B7-504	RUTHERFORD
S800	B7B-B-521	RUTHERFORD	T350	B7-502	RUTHERFORD
			T360 T361	B7-502 B7-504	RUTHERFORD RUTHERFORD
	THERMISTOR		T500	B7-D-500	RUTHERFORD
RT500	0.5-4 Ω	25W	T600	#45753	TRIAD
				FERRITE BEAD	
	TRANSFORMERS		FB400	56-590-65/3B	FERROXCUBE
T130	B7-501	RUTHERFORD	FB450	56-590-65/3B	FERROXCUBE
T210	B7-501	RUTHERFORD	FB460	56-590-65/3B	FERROXCUBE

REPLACEMENT OF COMPONENTS

In the event that component replacement becomes necessary, it is strongly recommended, in order to avoid considerable delay and unnecessary expense, that such replacement components be purchased from your local electronics supplier. A large majority of the components used in the instrument are standard electronic components and little difficulty should be encountered in replacing them.

Certain components, manufactured to RUTHERFORD ELECTRONICS CO.'S specifications, may not be readily available through local suppliers. These components should be ordered from our factory.

MANUAL AND REPAIR PARTS: When ordering a manual please indicate the instrument model number and its serial number and date of original purchase. For spare parts we suggest, (1) a careful description of the part, (2) the model number and serial number of the instrument and date of original purchase. If possible, please identify parts in relation to the schematic, giving data shown on the circuit schematic diagram.

WARRANTY


RUTHERFORD ELECTRONICS CO. guarantees to the original purchaser for a period of one (1) year, EXCEPT vacuum tubes which are guaranteed for ninety days, that this instrument is free from

defects in material and workmanship. Our liability is limited to repair or replacement of this instrument, or any part thereof, providing failure is not due to misuse of abnormal conditions.

In order to receive service under this warranty, promptly advise the factory of all details pertinent to failure of the instrument. Replacement parts will be shipped via air transportation if requested, prepaid to any point in the continental United States. Should it be desirable to return the instrument, ship it prepaid to the factory, and it will be serviced as required and returned via surface transportation, prepaid.

The RUTHERFORD ELECTRONICS CO. reserves the right not to honor warranty on any instrument with modifications done by the user. Before modifying, it is suggested that the modification be forwarded to the RUTHERFORD ELECTRONICS CO. for their approval, if it is desired to keep the instrument in its remaining warranty period. Send a schematic of the circuit under modification and an explanation of what will be done. In return, the RUTHERFORD ELECTRONICS CO. will evaluate your proposal and inform you as to its warranty position.

Service required after the expiration of warranty, or because of misuse or abnormal conditions will be billed at cost.













Rutherford
BLOCK DIAGRAM
2.2.60 87B-107
DR. V. S. APP. *DW*

LTR	DATE	CO NO	BY

WAVEFORMS

PULSE GENERATOR SETTING: REP. RATE 2 MC
 DELAY 0.1 μ SEC
 WIDTH 0.15 μ SEC
 OSCILLOSCOPE SETTING: TIME/CM 0.1 μ SEC
 (TEKTRONIX TYPE 541A) VOLTS/CM AS SPECIFIED










WAVEFORMS
OSCILLOSCOPE SETTING:
(TEKTRONIX TYPE 541A)
VOLTS/CM AS SPECIFIED
TIME/CM 0.1 MSEC
WIDTH 0.15 MSEC
DELAY 0.1 MSEC
REPEAT RATE 5 MC


GREATER THAN ONE (1) ARE IN MICROMICROFARADS.



C	6-14-61	381	V. S.	<i>BU</i>
B	9-21-60	284	V. S.	<i>BU</i>
A	8-25-60	282	V. S.	<i>BU</i>
LTR	DATE	C. O. NO	BY	APP.



PULSE GENERATOR SETTING: REP. RATE 2 MC
 DELAY 0.1 μ SEC
 WIDTH 0.15 μ SEC
 OSCILLOSCOPE SETTING: TIME/CM 0.1 μ SEC
 (TEKTRONIX TYPE 541A) VOLTS/CM AS SPECIFIED





NOTES: UNLESS OTHERWISE SPECIFIED,

1. ALL FIXED RESISTORS ARE 1/2 WATT, $\pm 10\%$.
2. ALL CAPACITOR VALUES ONE (1) OR LESS ARE IN MICROFARADS, THOSE GREATER THAN ONE (1) ARE IN MICROMICROFARADS
3. POLARITY SWITCH, S450, SHOWN IN THE POSITIVE (+) OUTPUT PULSE POSITION.
4. STEP ATTENUATOR SWITCH, S800, SHOWN IN THE (0) DB. ATTENUATION POSITION.



Rutherford
ELECTRONICS CO.
CULVER CITY, CALIF.

PULSE FORMING & OUTPUT SECT.


MODEL B7B PULSE GENERATOR
6/24/60 B7B-111F
DR. BY V. S. APP. BY J. Ward SER.

F	6-14-61	381	V. S.	EW
E	3-21-61	350	V. S.	EW
D	12-15-60	337	V. S.	PD
C	9-30-60	287	V. S.	
B	9-21-60	284	V. S.	EW
A	8-25-60	282	V. S.	EW
LTR	DATE	C. O. NO.	BY	APP.

NOTES: UNLESS OTHERWISE SPECIFIED,

1. ALL FIXED RESISTORS ARE 1/2 WATT, $\pm 10\%$.

2. ALL CAPACITOR VALUES ONE (1) OR LESS ARE IN MICROFARADS, THOSE GREATER THAN ONE (1) ARE IN MICROMICROFARADS.



Rutherford



MODEL B9/A9

PULSE

A N D

TIME DELAY SYSTEMS

A 9 - 0 0 1

The Rutherford Model A9 Time Delay Systems and Model B9 Pulse Generating Systems represent a dynamic new approach to pulse and time delay circuitry. The Model A9-001 features all new transistorized circuitry, to make it the finest, most reliable, highly accurate time delay generator available today.

SPECIFICATIONS:

MODEL A9-001

DELAY: The Model A9-001 is a highly accurate time delay generator which exhibits the following characteristics:

RANGE: The output pulse may be delayed continuously from 0.8 to 100,000 microseconds (with respect to the input trigger) in five ranges:

- 0.8 microseconds to 10 microseconds
- 10 microseconds to 100 microseconds
- 100 microseconds to 1,000 microseconds
- 1,000 microseconds to 10,000 microseconds
- 10,000 microseconds to 100,000 microseconds

ACCURACY: The delay dial setting is accurate to the following tolerances, except for the 0.8 to 10 microseconds range for which no accuracy tolerance is specified:

After calibration: $\pm 0.1\%$ of full scale.

JITTER: Time jitter introduced by the generator is less than 0.006% of full scale or 0.01 microseconds, whichever is greater.

DUTY FACTOR EFFECTS: Errors in delay may be introduced with increased duty factors. The table below indicates approximate error at various duty factors on the 100 to 1,000 microsecond range:

Duty Factor	Error	Duty Factor	Error
.02	Ref.	.75	3.6%
.05	1.01%	.90	5.1%
.20	0.6%	.95	6.4%
.50	2.2%		

Note: The duty factor must be limited to allow at least 3 microseconds recovery time.

LINE VOLTAGE VARIATION EFFECTS: A change of line voltage from 105 to 125 volts, RMS, changes the delay by 0.15%, maximum.

TEMPERATURE VARIATION EFFECTS: A change in ambient temperature will have the following effect on time delay:

0.8 to 10 microsecond range—a delay drift of 1% of full scale, maximum, over the range of 0°C. to +35°C.

All other ranges—a delay drift of 0.5% of full scale, maximum, over the range of -10°C. to +50°C.

MODULATION: Delay may be modulated by the introduction of an external voltage. A 2.8 to 12 volt change will vary the delay from minimum to maximum on any range.

MISCELLANEOUS:

POWER REQUIRED: 105 to 125 volts, 0.35 amps., 50 to 60 cps., 40 watts

WEIGHT: Approx. 55 lbs., Shipping—Approx. 60 lbs.

DIMENSIONS: 10½" high x 22" wide x 15" deep

PRICE: \$1,155.00 F.O.B. Culver City, California

OUTPUTS:

The following output wave forms are available at the front panel jacks.

BLOCKING OSCILLATOR OUTPUT: The blocking oscillator output occurs at the end of the time delay setting and exhibits the following characteristics:

- Amplitude: 30 volts, peak, minimum
- Rise Time: .030 microseconds, maximum
- Width: .1 microseconds, minimum
- Polarity: Positive.
- Output Impedance: 50 ohms
- Blocking Capacitor: .01 microfarad

MULTIVIBRATOR OUTPUT: A multivibrator output which occurs at the end of the time delay setting is provided for conveniently viewing the delay on an oscilloscope at slow sweep speeds. It exhibits the following characteristics:

Amplitude: 12 volts, peak, minimum Width:

Delay Range	Width
0.8 to 10 microseconds	Approx. 0.5 microsecond
100 microseconds	Approx. 5 microseconds
1,000 microseconds	Approx. 36 microseconds
10,000 microseconds	Approx. 120 microseconds
100,000 microseconds	Approx. 350 microseconds

- Polarity: Positive
- Output Impedance: 2K ohms
- Blocking Capacitor: .01 microfarad

GATE OUTPUT: A gate output is provided which turns on with the input trigger and off at the end of the time delay. It exhibits the following characteristics:

- Amplitude: 10 volts, peak, minimum
- Polarity: Positive
- Output Impedance: 100 ohms

RAMP OUTPUT: A ramp output is provided which starts with the trigger and turns off at the end of the time delay. It exhibits the following characteristics:

- Amplitude: +3 to +12 volts
- Polarity: Positive—going with delay.
- Output Impedance: 470 ohms

INPUT TRIGGER: The following trigger is required from an external source to initiate the time delay.

PULSE: The unit may be triggered by a pulse exhibiting the following characteristics:

- Amplitude: 5 to 60 volts, peak
- Width: 0.05 microseconds or greater
- Polarity: Positive or Negative
- Frequency: Single shot to 290KC

Note Duty cycle limitation

SINE WAVE: The unit may also be triggered by a sine wave exhibiting the following characteristics:

- Amplitude: 10-70 volts, peak to peak
- Frequency: 5 cps to 290 KC

A trigger sensitivity control allows reliable triggering from an external source, regardless of waveform.

INPUT IMPEDANCE: 50K ohms, blocking capacitor for 100 volts

All data subject to change without notice.

Bulletin No. 618

Representatives and Service in the major cities of the World

accurate research start
with **RUTHERFORD**
pulse instrumentation

Rutherford
ELECTRONICS CO.

8944 Lindblade Street
Culver City, California
Telephone: UPTon 0-7393
TWX-CVR-CY-4133

pulse generators / pulse systems / accurate time delay generators

Rutherford ELECTRONICS CO.

8944 Lindblade Street • Culver City, California
Telephone: Upton 0-7393 • TWX CVR-CY-4133

ACCESSORY ASSEMBLIES

PRINTED IN U.S.A.
AUGUST 1, 1960

Rutherford accessories are precisely designed to enhance greater efficiency and performance, ease of operation for use in pulse instrumentation

PART NO.	DASH NO.	N A M E	D E S C R I P T I O N	P R I C E
J001	-1	Extension Cable, Coax. 185 ohms (RG 114/u) Type C Connector, Both Ends	6 in. long	\$17.50
	-2		10 in. long	17.50
	-3		20 in. long	17.50
	-4		24 in. long	17.50
	-5		48 in. long	19.50
	-6		96 in. long	19.50
J002	-1	Extension Cable, Coax. 185 ohms (RG 114/u) Type C Connector, One end, Open Other End	24 in. long	10.00
	-2		48 in. long	10.00
	-3		60 in. long	10.50
	-4		96 in. long	10.50
J003	-1	Extension Cable, Coax. 50 ohms (RG 58/u) Type BNC Connector, Both Ends	12 in. long	5.00
	-2		24 in. long	5.00
	-3		48 in. long	5.50
	-4		96 in. long	5.50
J004	-1	Extension Cable, Coax. 50 ohms (RG 58/u) Type BNC Connector, One End, Open Other End	12 in. long	2.50
	-2		24 in. long	2.50
	-3		48 in. long	3.50
	-4		96 in. long	3.50
J005	-1	Extension Cable, Coax. 50 ohms (RG 58/u) Type N Connector, Both Ends	24 in. long	9.50
	-2		48 in. long	10.00
	-3		96 in. long	10.00
J006	-1	Extension Cable, Coax. 50 ohms (RG 58/u) Type N Connector, One End, Open Other End	24 in. long	5.00
	-2		48 in. long	5.50
	-3		96 in. long	5.50
J007	-1	Extension Cable, Coax. 50 ohms (RG 58/u) Type UHF Connector, Both Ends	12 in. long	4.50
	-2		24 in. long	4.50
	-3		48 in. long	5.00
	-4		96 in. long	5.00
J008	-1	Extension Cable, Coax. 50 ohms (RG 58/u) Type UHF Connector, One End, Open Other End	12 in. long	2.50
	-2		24 in. long	2.50
	-3		48 in. long	3.00
	-4		96 in. long	3.00
J009	-1	Extension Cable, Coax. 93 ohms (RG 62/u) Type BNC Connector, Both Ends	12 in. long	9.00
	-2		24 in. long	9.00
	-3		48 in. long	9.50
	-4		96 in. long	9.50
J010	-1	Extension Cable, Coax. 93 ohms (RG 62/u) Type BNC Connector, One End, Open Other End	12 in. long	4.50
	-2		24 in. long	4.50
	-3		48 in. long	5.50
	-4		96 in. long	5.50

PART NO.	DASH NO.	NAME	DESCRIPTION	PRICE
J011	-1	Extension Cable, Coax. 93 ohms (RG 62/u) Type UHF Connector, Both Ends	12 in. long	4.50
	-2		24 in. long	4.50
	-3		48 in. long	5.50
	-4		96 in. long	5.50
J012	-1	Extension Cable, Coax. 93 ohms (RG 62/u) Type UHF Connector, One End, Open Other End	12 in. long	2.50
	-2		24 in. long	2.50
	-3		48 in. long	3.50
	-4		96 in. long	3.50
J014		Extension Cable, 16 Wire, Amphenol 26-4100-16P Plug, One End, 26-4200-16S Socket, Other End	40 in. long. Extension Cable to be used with Model B3 and Model B5 Systems	15.00
J015		Extension Cable, 11 wire, Amphenol #86 PM11 Plug, One End, #78 PF11 Socket, Other End	24 in. long. Extension Cable to be used with Model B2 and B2A Pulse Generators	9.00
J017	-1	Adapter	 Adapter, Banana Plug to Type BNC Coax. Connector, Non-Locking	6.50
	-2	Adapter	 Adapter, Banana Plug to Type BNC Coax. Connector, Lock-on Type	7.50
	-3	Adapter	 Adapter, Banana Plug to Type UHF Coax. Connector, Lock-on Type	7.50
	-4	BNC Binding Post Adapter	 Can be used to adapt the Single Shot Pulse Generator to the B-5A 10 MC Pulse Generator.	7.50
J018		"One-Shot" Pulse Generator	 "One-Shot" Push Button Actuated Pulse Generator. Suitable for Single Pulse Operation of Model B7 Pulse Generator. 18 Volt Pulse into 470 ohms Mounts in Standard Banana Jacks	47.50
J019	-1	Air Filter End Cover	 Replaces Intake End Cover on Model B7 Pulse Generator to Prevent Excessive Dust from Entering Instrument. Filter Removable for Cleaning or Replacement	18.00
	-2	Air Filter End Cover	Same as -1, Except for Model B7B Pulse Generator	18.00
J013		Mixer Assembly	 "Two Input" Mixer Assembly for B3 System	55.00
J032	-1	Mixer Assembly	 "Two Input" Mixer Assembly for Model B7 or B7B. Maximum Input Power Each, Input 30 Watts Average. Impedance 50 ohms	45.00
	-2	Mixer Assembly	 "Three Input" Mixer Assembly for Model B7 or B7B. Maximum Input Power Each, Input 30 Watts Average. Impedance 50 ohms	60.00
	-3	Mixer Assembly	 "Four Input" Mixer Assembly for Model B7 or B7B. Maximum Input Power Each, Input 30 Watts Average. Impedance 50 ohms	75.00

INSTRUCTION MANUALS

NOTE: Serial Numbers of Instrument Must Be Included
When Reordering Instruction Manuals

PART NO.	DASH NO.	NAME	DESCRIPTION	PRICE
J020		Instruction Manual	For Model A2 or Model A4 Time Delay Generator	5.00
J021	-1*	Instruction Manual	For Model B2 Pulse Generator	7.50
	-2		For Model B2A Pulse Generator	7.50
J022*	-1	Instruction Manual	For Model B3 Pulse Generator	7.50
	-2		For Model B3-2 Pulse Generator	10.00
	-3		For Model B3-2A Pulse Generator	10.00
	-4		For Model B3-3 Pulse Generator	10.00
	-5		For Model B3-4 Pulse Generator	10.00
J023*		Instruction Manual	For Model B4 Time Measuring System	7.50
J024	-1*	Instruction Manual	For Model B5 Pulse Generator	7.50
	-2		For Model B5A Pulse Generator	7.50
	-3		For Model B5-2 Pulse Generator	10.00
J025	-1*	Instruction Manual	For Model B7 Pulse Generator	5.00
	-2		For Model B7B Pulse Generator	5.00
J026*		Instruction Manual	For Model D2 Calibrator	7.50
J027*		Instruction Manual	For Model G1 Pulse and Sq. Wave Generator	7.50
J028		Instruction Manual	For Model J018 "One-Shot" Pulse Generator	3.00


*Indicates Instrument No Longer In Production, But Manuals For Existing Instruments Available

INSTRUMENT MODIFICATION

PART NO.	DASH NO.	NAME	DESCRIPTION	PRICE
J029	-1	Modifies the Model B2A to Provide for External Delay and Width Modulation		115.00
	-2	Modifies the Model B2A to Provide for External Delay Modulation		65.00
J030		Modifies Model B2 to Configuration and Specification of the Model B2A		400.00
J031		Modifies Model A2 or Model A4 to Incorporate Special Delay Range Per Customer Requirement		60.00
J033		Modifies Model B5 to Model B5-A		1,000.00
J034		Modifies Model B5 to Model B5-2 Double Pulse Generator		3,073.00
J035		Modifies Model B5-A to Model B5-2 Double Pulse Generator		2,080.00
J036		Delay Cable Model B5-2		325.00


THE ACCESSORIES ARE DESIGNED TO COMPLEMENT

Rutherford PULSE INSTRUMENTATION




NEW MODEL B7-B HIGH REPETITION RATE PULSE GENERATOR AT LOW COST, HIGH PERFORMANCE and WIDE VERSATILITY

50 volts into 50 ohms at 30% duty factor... rep. rate to 2 mc... widths .05 μ s to 10,000 μ s... delays to 10,000 μ s... Low Budget Price... \$720.00



10 MEGACYCLE PULSE GENERATOR MODEL B5-A

Featuring... high repetition rate with no greater than 8 millimicroseconds rise and fall time operating from 1 cps to 10 megacycles.
Price: \$2,400.00



MODEL B2-A

A general purpose instrument which produces pulses of accurately controlled widths, amplitude and time delay at low impedance. Internal oscillator gives repetition rates from 10 cycles to 100 kc. Pulse widths from .08 μ s to 1,000 μ s.
Price: \$1,280.00



TWO TIME DELAY GENERATORS Model A-2


Feature: Low jitter. Linear scales. Small repetition rate effects. External connector provided for delay voltage so that unit may be externally time modulated. Easily read dial controls.

Price: Model A-2 \$750.00



Model A-4

Price: Model A-4 \$875.00



HIGH SPEED 10 MEGACYCLE DOUBLE PULSE GENERATOR MODEL B5-2

Both pulse trains are derived from one single oscillator. Its output pulses are adjustable in widths from 20 μ s to 12.5 μ s with rise and fall time no greater than 8 μ s. Maximum pulse width is restricted to about 20% of the pulse to pulse spacing. (Duty cycle .20 or less). Continuously variable repetition rate, pulse width and pulse delay permit the study of high speed switching circuits.
Price: \$3,975.00

MULTI-PULSE Rutherford HIGH REPETITION RATE MULTI-PULSING SYSTEM at low cost!

4 MODEL B7-B with the use of a MIXING NETWORK produces 4 INDIVIDUAL PULSES of various specifications. The stacked units may be placed in a 19" rack type cabinet. Each of the four B7-B models can be disassembled and returned to laboratories for use as individual pulse generators.

Price: \$720.00 each, MIXER ASSEMBLY - \$75.00



All prices F.O.B. Culver City, California

For detailed specifications on Rutherford pulse instrumentation write for complete bulletin.

REPRESENTATION AND SERVICE THROUGHOUT THE WORLD

AHEARN & SOPER CO. LTD.
850 Belfast Road
Elmhurst, Ontario
Ottawa, Canada

BROGER INSTRUMENT SALES CO., INC.
48 Pearl Street
Brookline 47, Mass.
Tel: Beacon 2-4804
TWX BKN-1073

BROGER INSTRUMENT SALES CO., INC.
P.O. Box 2917 (433 Winthrop Ave.)
New Haven 15, Connecticut
Tel: Spruce 7-6279

DAYTON ASSOCIATES
Suite 1318 Talbot Tower
118 West First Street
Dayton 2, Ohio
Tel: Baldwin 3-9621

DAYTON ASSOCIATES
4924 Zula Avenue
Cincinnati 38, Ohio
Tel: Blackburn 1-2349

DAYTON ASSOCIATES
3017 Snow Road
Cleveland 34, Ohio
Tel: Yellowstone 2-6655

THE LOWELL CO.
4124 Skokiana Terrace
Skokie, Illinois
Tel: Orchard 6-2063

FRAZAR & HANSEN, LTD.
301 Clay Street
San Francisco 11, California
EXPORT: Cable "Frasen" San Francisco
Tel: EXbrook 2-5112

LOUIS A. GARTEN & ASSOCIATES
375 Passaic Avenue
Caldwell, New Jersey
Tel: Capital 6-7800

LOUIS A. GARTEN & ASSOCIATES
730 Washington Lane
Jenkintown, Pennsylvania
Tel: Waverly 7-1200

THE HEIMANN COMPANY
1711 Hawthorne Avenue
Minneapolis 3, Minnesota
Tel: Federal 2-5457 TWX MP-426

THE HEIMANN COMPANY
6636 Agnes Street
Kansas City 30, Missouri
Tel: Jackson 3-2126

S. S. LEE ASSOCIATES, INC.
2521 Ennals Avenue
Wheaton, Maryland
Tel: Lockwood 5-3066
TWX Kensington, Md., 247

S. S. LEE ASSOCIATES, INC.
P.O. Box 205
Lutherville, Maryland
Tel: Valley 3-3434

S. S. LEE ASSOCIATES, INC.
P.O. Box 7896
Orlando, Florida
Tel: Garden 3-6566 TWX Or 7145

S. S. LEE ASSOCIATES, INC.
P.O. Box 906
Winston-Salem, North Carolina
Tel: State 8-0431

S. S. LEE ASSOCIATES, INC.
210 Terry-Hutchens Bldg.
Huntsville, Alabama
Tel: Je 6-0631

G. E. MOXON ELECTRONICS CO.
489 So. Robertson Blvd.
Beverly Hills, California
Tel: Bradshaw 2-9311
TWX BV-6744

G. E. MOXON ELECTRONICS CO.
15 West 41st Street
San Mateo, California
Tel: Fireside 5-7961

G. E. MOXON ELECTRONICS CO.
4434 Ingham Street
San Diego, California
Tel: Hudson 8-2901

NACO ELECTRONICS CORP.
119 Luther Ave.
Liverpool, New York
Tel: GR 4-7481 TWX SS-265

NACO ELECTRONICS CORP.
74 Park Ave.
Rochester, New York
Tel: Greenfield 3-4169

NACO ELECTRONICS CORP.
Stanley Theatre Bldg.
261 Genesee St.
Utica, New York
Tel: Redwood 2-3151

N. R. SCHULTZ COMPANY
4227 Airport Way
Seattle 8, Washington
Tel: Main 4-8650

TOWER ENGINEERING CO.
19364 James Couzens
Detroit 35, Michigan
Tel: Di 1-2332

WILLIAMS & ASSOCIATES, INC.
2261 So. Albion Street
Denver 22, Colorado
Tel: Skyline 6-9403 TWX DN-134

WILLIAMS & ASSOCIATES, INC.
3221 Silver Avenue, S.E.
Albuquerque, New Mexico
Tel: Alpine 5-9632

WILLIAMS & ASSOCIATES, INC.
320 E. 4th South Street
Salt Lake City, Utah
Tel: Empire 4-6844

N. S. BROWN ASSOCIATES
5852 Boca Raton Drive
Dallas 30, Texas
Tel: EM 3-3698

PART NUMBERS FOR TERMINATIONS

PART NO.	CONNECTORS	IMPEDANCE	WATTAGE	PRICE	PART NO.	CONNECTORS	IMPEDANCE	WATTAGE	PRICE
K001-1	N (Male)	50 ohms	2*	35.00	K002-11	C (Male)	50 ohms	5*	40.00
K001-2	N (Male)	75 ohms	2*	37.50	K002-12	C (Male)	75 ohms	5*	42.00
K001-3	N (Male)	93 ohms	2*	37.50	K002-13	C (Male)	93 ohms	5*	42.00
K001-4	N (Male)	125 ohms	2*	39.00	K002-14	C (Male)	125 ohms	5*	45.00
K001-5	N (Male)	185 ohms	2*	39.00	K002-15	C (Male)	185 ohms	5*	45.00
K001-6	N (Female)	50 ohms	2*	35.00	K002-16	C (Female)	50 ohms	5*	40.00
K001-7	N (Female)	75 ohms	2*	37.50	K002-17	C (Female)	75 ohms	5*	42.00
K001-8	N (Female)	93 ohms	2*	37.50	K002-18	C (Female)	93 ohms	5*	42.00
K001-9	N (Female)	125 ohms	2*	39.00	K002-19	C (Female)	125 ohms	5*	45.00
K001-10	N (Female)	185 ohms	2*	39.00	K002-20	C (Female)	185 ohms	5*	45.00
K001-11	C (Male)	50 ohms	2*	35.00	K003-1	N (Male)	50 ohms	10*	42.50
K001-12	C (Male)	75 ohms	2*	37.50	K003-2	N (Male)	75 ohms	10*	45.00
K001-13	C (Male)	93 ohms	2*	37.50	K003-3	N (Male)	93 ohms	10*	45.00
K001-14	C (Male)	125 ohms	2*	39.00	K003-4	N (Male)	125 ohms	10*	48.00
K001-15	C (Male)	185 ohms	2*	39.00	K003-5	N (Male)	185 ohms	10*	48.00
K001-16	C (Female)	50 ohms	2*	35.00	K003-6	N (Female)	50 ohms	10*	42.50
K001-17	C (Female)	75 ohms	2*	37.50	K003-7	N (Female)	75 ohms	10*	45.00
K001-18	C (Female)	93 ohms	2*	37.50	K003-8	N (Female)	93 ohms	10*	45.00
K001-19	C (Female)	125 ohms	2*	39.00	K003-9	N (Female)	125 ohms	10*	48.00
K001-20	C (Female)	185 ohms	2*	39.00	K003-10	N (Female)	185 ohms	10*	48.00
K002-1	N (Male)	50 ohms	5*	40.00	K003-11	C (Male)	50 ohms	10*	42.50
K002-2	N (Male)	75 ohms	5*	42.00	K003-12	C (Male)	75 ohms	10*	45.00
K002-3	N (Male)	93 ohms	5*	42.00	K003-13	C (Male)	93 ohms	10*	45.00
K002-4	N (Male)	125 ohms	5*	45.00	K003-14	C (Male)	125 ohms	10*	48.00
K002-5	N (Male)	185 ohms	5*	45.00	K003-15	C (Male)	185 ohms	10*	48.00
K002-6	N (Female)	50 ohms	5*	40.00	K003-16	C (Female)	50 ohms	10*	42.50
K002-7	N (Female)	75 ohms	5*	42.00	K003-17	C (Female)	75 ohms	10*	45.00
K002-8	N (Female)	93 ohms	5*	42.00	K003-18	C (Female)	93 ohms	10*	45.00
K002-9	N (Female)	125 ohms	5*	45.00	K003-19	C (Female)	125 ohms	10*	48.00
K002-10	N (Female)	185 ohms	5*	45.00	K003-20	C (Female)	185 ohms	10*	48.00

CONNECTORS: N (Male) = #UG 21D/U C (Male) = #UG 573A/U *1000 LFM per minute
N (Female) = #UG 23D/U C (Female) = #UG 572/U ALL DATA SUBJECT TO CHANGE WITHOUT NOTICE

PART NUMBERS FOR ATTENUATORS

PART NO.	CONNECTORS	ATTENUATORS (DB)	WATTAGE	PRICE
M001-1	N	1	4	30.00
M001-2	N	2	4	30.00
M001-3	N	5	4	30.00
M001-4	N	10	2	30.00
M001-5	N	20	1	40.00
M001-6	C	1	4	35.00
M001-7	C	2	4	35.00
M001-8	C	5	4	35.00
M001-9	C	10	2	35.00
M001-10	C	20	1	45.00
M002-1	N	1	15	45.00
M002-2	N	2	15	45.00
M002-3	N	5	10	50.00
M002-4	N	10	10	50.00
M002-5	N	20	5	60.00
M002-6	C	1	15	50.00
M002-7	C	2	15	50.00
M002-8	C	5	10	55.00
M002-9	C	10	10	55.00
M002-10	C	20	5	65.00

Rutherford ELECTRONICS CO.

8944 Lindblade Street Culver City, California Telephone: UPTon O-7393 TWX-CVR-CY-4133

Represented in Your Area by...





www.manualsplus.com



1026962

SE Laboratories
LOG- U2
MAN - 03307